

LED Pro-Rio Downlight drivers

# 42200001

EAN: 8720615503421

### CREATE AN INVITING ATMOSPHERE

The Prolumia LED accent lighting has two important functions. Firstly, it helps people find their way. Secondly, it creates fascinating light effects. Therefore light solutions can be created that are energy saving and it can also be divided to your own personal vision and taste. From showcase to entrance hall, useful for every field of application!



### PRODUCT FEATURES

Model	Static	Output voltage	60 60 Volt
Suitable for outdoor use	✘	Output current	500 500 Milliampere
Dimming 0-10 V	✘	Output power	19 19 Watt
Dimming 1-10 V	✘	Length	100 Millimetre
Dimming DALI	✘	Width	42.8 Millimetre
Dimming DMX	✘	Height	22.5 Millimetre
Dimming DSI	✘		
Dimming GPRS	✘		
Dimming LineSwitch	✘		
Dimming mains voltage modulation	✘		
Dimming manufacturer's proprietary system	✘		
Dimming phase cut-off (trailing edge)	✘		
Dimming phase cut-on (leading edge)	✘		
Dimming potentiometer (integrated)	✘		
Dimming programmable	✘		
Dimming RF	✘		
Dimming Sine Wave Reduction	✘		
Dimming Touch and Dim	✘		
Dimming with push-button	✘		
Dimming Zigbee	✘		
No dim function	✓		
Constant light output (CLO)	✘		
Housing	Plastic housing		
Suitable for constant current	✓		
Suitable for constant voltage	✘		
Suitable for DC-voltage (primary side)	✘		
Degree of protection (IP)	IP20		
Protection class according to IEC 61140	II		
Operation by Bluetooth	✘		
Compatible with Apple HomeKit	✘		
Compatible with Google Assistant	✘		
Compatible with Amazon Alexa	✘		
Compatible with Casambi	✘		
IFTTT support available	✘		

## LED Downlight (accent lighting)

PAGE 2/2

LED Pro-Rio Downlight drivers

# 42200001

EAN: 8720615503421

### PRODUCT FEATURES

(continuation)